



IONOS WORCESTER V6

Worcester, WR4 0AD, United Kingdom | Richard Williams | 29 Apr 2021



SYSTEM OVERVIEW

 1399 PV modules

 5 Inverters

 700 Optimizers

SIMULATION RESULTS



Installed DC Power
524.63 kWp



Max Achieved AC Power
381.20 kW



Annual Energy Production
441.22 MWh



CO2 Emission Saved
123.98 t



Equivalent Trees Planted
5,694



Max Achieved DC Power
457.68 kW



DC/AC Oversizing
120 %



Max Active AC Power
381.20 kW



Performance Ratio
89 %




Performance Index
841 kWh/kWp

IONOS WORCESTER V6

Worcester, WR4 0AD, United Kingdom | Richard Williams | 29 Apr 2021



ESTIMATED MONTHLY ENERGY



Total clipped energy: 0.07%

Month	Solar Production (kWh)	Consumption (kWh)	Self-consumption (kWh)	Clipped Energy (kWh)
Jan	9,175	-	-	-
Feb	14,738	-	-	-
Mar	33,584	-	-	-
Apr	54,523	-	-	101
May	64,863	-	-	3
Jun	68,359	-	-	197
Jul	64,138	-	-	7
Aug	51,934	-	-	-
Sep	37,916	-	-	1
Oct	23,877	-	-	-
Nov	11,153	-	-	-
Dec	6,955	-	-	-

PV MODULES

# Module	Model	Peak power	Racking type	Orientation	Azimuth	Tilt
598	Longi Solar, LR4-60HPH-375M	224.3 kWp			195°	10°

IONOS WORCESTER V6

Worcester, WR4 0AD, United Kingdom | Richard Williams | 29 Apr 2021

PV MODULES (CONTINUED)

# Module	Model	Peak power	Racking type	Orientation	Azimuth	Tilt
87	Longi Solar, LR4-60HPH-375M	32.6 kWp			285°	15°
116	Longi Solar, LR4-60HPH-375M	43.5 kWp			104°	6°
598	Longi Solar, LR4-60HPH-375M	224.3 kWp			15°	10°
Total: 1399		524.6 kWp				

BILL OF MATERIALS (BOM)

Items	Quantity
 SE82.8K	4
 SE50K	1
 P801	700
 Longi Solar, LR4-60HPH-375M	1399

ELECTRICAL DESIGN

Inverters & Storage	Strings per inverter	Optimizers per string	PV modules per string
 1 x SE82.8K 99.87kW 121%	Primary unit		
	∩ 1 x string	 15 x P801 (2:1)	 30
	∩ 2 x strings	 16 x P801 (2:1)	 32
	Secondary unit 1		
	∩ 1 x string	 15 x P801 (2:1)	 30
	∩ 2 x strings	 16 x P801 (2:1)	 32
	Secondary unit 2		
	∩ 1 x string	 15 x P801 (2:1)	 30
∩ 2 x strings	 16 x P801 (2:1)	 32	

IONOS WORCESTER V6

Worcester, WR4 0AD, United Kingdom | Richard Williams | 29 Apr 2021

ELECTRICAL DESIGN (CONTINUED)

Inverters & Storage	Strings per inverter	Optimizers per string	PV modules per string
 1 x SE82.8K 101.78kW 123%	Primary unit		
	∅ 1 x string	 18 x P801 (2:1)	 36
	∅ 2 x strings	 19 x P801 (2:1)	 38
	Secondary unit 1		
	∅ 3 x strings	 19 x P801 (2:1)	 38
	Secondary unit 2		
	∅ 1 x string	 18 x P801 (2:1)	 36
∅ 2 x strings	 19 x P801 (2:1)	 38	
 1 x SE82.8K 96.14kW 116%	Primary unit		
	∅ 3 x strings	 18 x P801 (2:1)	 36
	Secondary unit 1		
	∅ 1 x string	 15 x P801 (2:1)	 30
	∅ 1 x string	 17 x P801 (2:1)	 34
	∅ 1 x string	 19 x P801 (2:1)	 38
	Secondary unit 2		
	∅ 1 x string	 14 x P801 (2:1)	 28
	∅ 1 x string	 14 x P801 (2:1), 1 x P801 (1:1)	 29
	∅ 1 x string	 18 x P801 (2:1)	 36
 1 x SE82.8K 99.69kW 120%	Primary unit		
	∅ 1 x string	 15 x P801 (2:1)	 30
	∅ 1 x string	 16 x P801 (2:1)	 32
	∅ 1 x string	 19 x P801 (2:1)	 38
	Secondary unit 1		
	∅ 1 x string	 15 x P801 (2:1)	 30
	∅ 1 x string	 16 x P801 (2:1)	 32
	∅ 1 x string	 19 x P801 (2:1)	 38
	Secondary unit 2		
	∅ 1 x string	 16 x P801 (2:1)	 32
∅ 1 x string	 18 x P801 (2:1)	 36	
∅ 1 x string	 19 x P801 (2:1)	 38	

IONOS WORCESTER V6

Worcester, WR4 0AD, United Kingdom | Richard Williams | 29 Apr 2021

ELECTRICAL DESIGN (CONTINUED)

Inverters & Storage	Strings per inverter	Optimizers per string	PV modules per string
 1 x SE50K 60.2kW 120%	Primary unit		
	Ω 3 x strings	 14 x P801 (2:1)	 28
	Secondary unit 1		
	Ω↑ 2 x strings	 14 x P801 (2:1)	 28
	Ω↑ 1 x string	 15 x P801 (2:1)	 30

SYSTEM LOSS DIAGRAM



IONOS WORCESTER V6

Worcester, WR4 0AD, United Kingdom | Richard Williams | 29 Apr 2021



SIMULATION PARAMETERS



LOCATION & GRID

Time zone	BST (London)
Weather station	Worcester (4.69 km away)
Station altitude	27 m
Station data source	Meteonorm 7.1
Grid	400V L-L, 230V L-N



LOSS FACTORS

Near shading	Enabled
Albedo	0.20
Soiling/Snow	0%
Incidence angle modifier (IAM), ASHRAE b0 param.	0.05
Thermal loss factor U_c (const) Flush mount	20
Thermal loss factor U_c (const) Tilted	29
LID loss factor	0%
System unavailability	0%